

THE OPTIMAL FILTERING OF MARKOV JUMP
PROCESSES IN ADDITIVE WHITE NOISE

by

M. Zakai

15 June 1965

Research Note No. 563

Applied Research Laboratory
Sylvania Electronic System
A Division of Sylvania Electric Products Inc.
Waltham, Massachusetts 02154

The optimal filtering of Markov jump
processes in additive white noise.

This note is based on Wonham [1]. The differences between this note and [1] are discussed in Section VIII.

I. Statement of the Problem.

Let $x(t)$ be Markov jump process with stationary transition probabilities and with a finite number of states. Let $a_1, a_2, \dots, a_K$ be the states, let $p_{ij}(h)$ be the transition probabilities

$$p_{ij}(h) = \text{Prob} \left\{ x(t+h) = a_j \mid x(t) = a_i \right\}.$$

Let

$$p_{ij}(h) = \begin{cases} 1 - \nu_i h + o(h) & i=j, \quad h \searrow 0 \\ \nu_{ij}(h) + o(h) & i \neq j, \quad h \searrow 0 \end{cases}$$

where $\nu_i > 0$, $\nu_{ij} \geq 0$ and $\nu_i = \sum_{\substack{j=1 \\ i \neq j}}^K \nu_{ij}$, $i = 1, \dots, K$.

Let $p_i(0)$ be the initial distribution of $x(0)$. In addition let $y(t)$ be a process given by

$$dy(t) = x(t) dt + \beta dw(t), \quad y(0) = 0$$

where β is known and $w(t)$ is a standard Brownian motion. The problem is to find

$$p_j(t) = \text{Prob} \left\{ x(t) = a_j \mid \pi_0^t y(\cdot) \right\}$$

where $\pi_a^b y(\cdot)$ stands for $y(s)$, $a \leq s \leq b$.

II. A general expression for $p_j(t)$

The conditional probability $\text{Prob} \left\{ x(t) = a_j \mid A \right\}$ (where A is some condition) is the same as the conditional expectation of the function δ_{ij} (j fixed) given A . Applying Doob's theorem 8.8 ([2, p.21]), there exists a sequence $t_1, t_2, \dots$, all in $[0, t]$, such that a.s.

$$p_j(t) = \text{Prob} \left\{ x(t) = a_j \mid y(t_1), y(t_2), \dots \right\}$$

and by the martingale convergence theorem ([2, Cor 1 p.332]) a.s.

$$p_j(t) = \lim_{n \rightarrow \infty} \theta_j^{(n)}(t) \tag{1}$$

where $\theta_j^{(n)}(t) = \text{Prob} \left\{ x(t) = a_j \mid y(t_1), y(t_2), \dots, y(t_n) \right\}$.

In the following we will use:

$$\text{Prob} \left\{ x(t) \in A \mid \pi_0^t y(\cdot) \in B \right\} = \frac{\text{Prob} \left\{ x(t) \in A, \pi_0^t y(\cdot) \in B \right\}}{\text{Prob} \left\{ \pi_0^t y(\cdot) \in B \right\}}.$$

Consider now a fixed t_μ , $0 < t_\mu < t$; let $p_j(t \mid y(t_\mu))$ be the probability that $x(t) = a_j$ given $y(t_\mu)$ and let ξ_μ be

$$\xi_\mu = \int_0^{t_\mu} x(t) dt.$$

Then

$$p_j \left(t \mid y(t_\mu) \right) = \frac{\sum_{i=1}^K p_i(0) p_{ij}(t) \int_{-\infty}^{\infty} P_1(y(t_\mu) - \xi_\mu) P_2(\xi_\mu \mid x(0) = a_i, x(t) = a_j) d\xi_\mu}{\sum_{j=1}^K (\text{The same expression as in the numerator})}.$$

Note that P_1 is normal $(0, \beta^2 t_\mu)$. Let $\tilde{x}(t)$ be a process independent of $x(t)$ and $w(t)$ with the same law as $x(t)$. Let $\tilde{\xi}(s) = \int_0^s \tilde{x}(t) dt$, then

$$p_j \left(t \mid y(t_\mu) \right) = \frac{\sum_{i=1}^K p_i(0) p_{ij}(t) E \left\{ \exp \left[-\frac{(y(t_\mu) - \tilde{\xi}(t_\mu))^2}{2\beta^2 t_\mu} \right] \mid \tilde{x}(0) = a_i, \tilde{x}(t) = a_j \right\}}{\sum_{j=1}^K \sum_{i=1}^K p_i(0) p_{ij}(t) E \left\{ \exp \left[-\frac{(y(t_\mu) - \tilde{\xi}(t_\mu))^2}{2\beta^2 t_\mu} \right] \mid \tilde{x}(0) = a_i, \tilde{x}(t) = a_j \right\}} .$$

The conditioning of the expectations in the above expression are all $\tilde{x}(s)$ paths which start at $s=0$ with a_i and terminate at $s=t$ in the state a_j . Now let $s_{r,n} = r \frac{t}{n}$, $r = 0, 1, \dots, n$.

Let

$$\begin{aligned} \eta_{r,n} &= y(s_{r+1,n}) - y(s_{r,n}) \\ \tilde{\xi}_{r,n} &= \int_{r \frac{t}{n}}^{(r+1) \frac{t}{n}} \tilde{x}(s) ds . \end{aligned}$$

Then by the same arguments as above

$$\begin{aligned} p_j \left(t \mid y(r \frac{t}{n}), r=0, 1, \dots, n \right) &= \\ &= \frac{\sum_{i=1}^K p_i(0) p_{ij}(t) E \left\{ \exp - \sum_{r=0}^{n-1} \frac{(\eta_{r,n} - \tilde{\xi}_{r,n})^2}{2\beta^2 t/n} \mid \tilde{x}(0) = a_i, \tilde{x}(t) = a_j \right\}}{\sum_{j=1}^K (\text{numerator})} . \end{aligned} \quad (2)$$

The argument of the exponential is

$$\sum_{r=0}^{n-1} \left(\eta_{r,n}^2 - 2\eta_{r,n} \tilde{\xi}_{r,n} + \tilde{\xi}_{r,n}^2 \right) \frac{1}{2\beta^2 t/n} .$$

The first term will be cancelled by the same term in the denominator. The last term converges a.s. as $n \rightarrow \infty$ to

$$\frac{1}{2\beta^2} \int_0^t \tilde{x}(t)^2 dt .$$

The middle term converges a.s. to

$$-\frac{1}{\beta^2} \int_0^t \tilde{x}(t) dy(t) .$$

We want to apply these results to the evaluation of the limit of the numerator of (2) as $n \rightarrow \infty$. In order to do that we have to show that if $f_n \rightarrow f$ as $n \rightarrow \infty$, then $E(f_n | \cdot) \rightarrow E(f | \cdot)$. Since

$$\begin{aligned} \exp - \left[\sum_{r=0}^{n-1} \left(-2\eta_{r,n} \tilde{\xi}_{r,n} + \tilde{\xi}_{r,n}^2 \right) \right] \\ \leq \exp \left[A_{\max}^2 \cdot t + 2A_{\max} \cdot \sup\{|y(t_1) - y(t_2)|, t_1, t_2 \in [0, t]\} \right] \end{aligned}$$

it follows, by dominated convergence that the limit of the numerator of (2), as $n \rightarrow \infty$, is

$$\psi_j(t) = \sum_{i=1}^K p_i(0) p_{ij}(t) E \left\{ \exp \left[-\frac{1}{2\beta^2} \int_0^t \tilde{x}^2(s) ds + \frac{1}{\beta^2} \int_0^t \tilde{x}(s) dy(s) \right] \mid \tilde{x}(0) = a_i, \tilde{x}(t) = a_j \right\} \quad (3)$$

and the conditioning is with respect to all the paths which start at $\tilde{x}(0) = a_i$ and terminate at $\tilde{x}(t) = a_j$. Similarly the limit of the denominator is $\sum_{j=1}^K \psi_j(t)$ where $\psi_j(t)$ is given by equation (3). Since $\psi_j(t) > 0$ a.s. we have

$$\lim_{n \rightarrow \infty} p_j \left(t \mid y \left(r \frac{t}{n} \right), r = 0, 1, \dots, n \right) = \frac{\psi_j(t)}{\sum_{i=1}^K \psi_i(t)}. \quad (4)$$

The limits (3) and (4) were obtained by a particular sequence of partitions of $[0, t]$, but it is clear that the same result will hold for any sequence of partitions $\{s_{r,n}\}$ such that $0 = s_{0,n} < s_{1,n} < \dots < s_{n,n} = t$ and such that $\max_r (s_{r+1,n} - s_{r,n}) \rightarrow 0$ as $n \rightarrow \infty$. We may therefore use a sequence for which (1) is true. Therefore

$$p_j(t) = \frac{\psi_j(t)}{\sum_{i=1}^K \psi_i(t)}. \quad (5)$$

III. The stochastic differential equation for $\psi_j(t)$.

Let $\psi_{i,j}(a, b)$, ($b > a$) be

$$\psi_{i,j}(a, b) = p_{ij}(b-a) E \left\{ \exp \left[-\frac{1}{2\beta^2} \int_a^b \tilde{x}^2(s) ds + \frac{1}{\beta^2} \int_a^b \tilde{x}(s) dy(s) \right] \mid \tilde{x}(a)=a_i, \tilde{x}(b)=a_j \right\} .$$

Then, comparing with (3):

$$\psi_j(t) = \sum_{i=1}^K p_i(0) \psi_{i,j}(0, t) .$$

Consider a fixed realization of $\pi_0^{t+h} y(\cdot)$, we prove now that

$$\psi_j(t+h) = \sum_{i=1}^K \psi_i(t) \cdot \psi_{i,j}(t, t+h) . \quad (6)$$

Proof:

$$\begin{aligned} & \psi_{i,j}(0, t+h) \\ &= p_{ij}(t+h) E \left\{ \exp \left[-\int_0^{t+h} \dots + \int_0^{t+h} \dots \right] \mid \tilde{x}(t+h)=a_j, \tilde{x}(0)=a_i \right\} \\ &= p_{ij}(t+h) \sum_{k=1}^K E \left\{ \exp \left[-\int_0^{t+h} \dots + \int_0^{t+h} \dots \right] \mid \tilde{x}(t+h)=a_j, \tilde{x}(t)=a_k, \tilde{x}(0)=a_i \right\} \\ & \quad \cdot \text{Prob} \left\{ \tilde{x}(t)=a_k \mid \tilde{x}(t+h)=a_j, \tilde{x}(0)=a_i \right\} . \end{aligned}$$

Since $\tilde{x}(t)$ is a Markov process, the conditional expectation becomes the product of two conditional expectations (since, given $\tilde{x}(t)$, $\tilde{x}(t-\alpha)$ and $\tilde{x}(t+\beta)$ are independent for $\alpha, \beta > 0$).

Moreover

$$\text{Prob} \left\{ \tilde{x}(t) = a_k \mid \tilde{x}(t+h)=a_j, \tilde{x}(0)=a_i \right\} = \frac{p_{ik}(t) p_{kj}(h)}{p_{ij}(t+h)} .$$

Therefore

$$\begin{aligned}
\psi_{i,j}(0, t+h) &= \sum_{k=1}^K p_{ik}(t) E \left\{ \exp \left[-\int_0^t \dots + \int_0^t \dots \right] \left| \tilde{x}(t) = a_k, \tilde{x}(0) = a_i \right. \right\} \\
&\quad \cdot p_{kj}(h) E \left\{ \exp \left[-\int_0^t \dots + \int_0^t \dots \right] \left| \tilde{x}(t+h) = a_j, \tilde{x}(t) = a_k \right. \right\} \\
&= \sum_{k=1}^K \psi_{i,k}(0, t) \cdot \psi_{k,j}(t, t+h)
\end{aligned}$$

which is the required result.

Since the $x(t)$ process is Markov and the $w(t)$ process has independent increments, it follows that $\psi_{i,k}(0, t)$ and $\psi_{k,j}(t, t+h)$ are conditionally independent given $x(t)$. Therefore the process $(x(t), \psi_1(t), \psi_2(t), \dots, \psi_K(t))$ is a $K+1$ dimensional Markov process.

$\psi_{i,j}(t, t+h)$ will now be evaluated for small h . Assuming that h is small enough so that the possibility that more than one transition in $[t, t+h]$ can be ignored we have

$$\begin{aligned}
\psi_{i,i}(t, t+h) &\cong (1 - \nu_i h) \exp \left[-\frac{a_i^2}{2\beta^2} h + \frac{a_i}{\beta^2} (y(t+h) - y(t)) \right] \\
\psi_{i,j}(t, t+h) &\cong \nu_{ij} h \exp \left[-\frac{a_j^2 h \theta_1}{2\beta^2} + \frac{a_j \theta_2}{\beta^2} (y(t+h) - y(t)) \right] \quad j \neq i
\end{aligned}$$

The factors θ_1 and θ_2 were included in the last expression in order to indicate that it is unknown where in $[t, t+h]$ the transition occurred; it will turn out that this is immaterial. Setting now $y(t+h) - y(t) = \int_t^{t+h} x(s) ds + \beta w(t+h) - \beta w(t)$ and expanding the exponential in a power series we obtain

$$\psi_{i,i}(t, t+h) \cong 1 - \nu_i h - \frac{a_i^2}{2\beta^2} h + \frac{a_i}{\beta^2} (y(t+h) - y(t)) + \frac{a_i^2}{2\beta^4} \beta^2 (w(t+h) - w(t))^2 + o_1(h, (\Delta_h w)^2)$$

where $o_1(h, (\Delta_h w)^2)$ denotes the terms omitted. Also

$$\psi_{i,j}(t, t+h) \cong \nu_{ij} h + o_2(h, (\Delta_h w)^2) .$$

Substituting into (6) we have

$$\begin{aligned} \psi_j(t+h) &= \psi_j(t) - \nu_j \psi_j(t) h - \frac{a_j^2}{2\beta^2} h \psi_j(t) + \frac{a_j \psi_j(t)}{\beta^2} (y(t+h) - y(t)) \\ &\quad + \frac{a_j^2}{2\beta^2} (w(t+h) - w(t))^2 + \sum_{\substack{i=1 \\ i \neq j}}^K \psi_i(t) \nu_{ij} h + o_3(h, (\Delta_h w)^2) . \end{aligned}$$

Therefore

$$\begin{aligned} \psi_j(t) - \psi_j(0) &= \int_0^t \left[-\nu_j \psi_j(s) + \sum_{\substack{i=1 \\ i \neq j}}^K \psi_i(s) \nu_{ij} - \frac{a_j^2 \psi_j(s)}{2\beta^2} \right] ds \\ &\quad + \int_0^t \frac{a_j \psi_j(s)}{\beta^2} dy(s) + \lim_{h \rightarrow 0} \sum_{r=1}^{t/h} \frac{a_j^2 \psi_j(hr)}{2\beta^2} (w((r+1)h) - w(rh))^2 \\ &\quad + \lim_{h \rightarrow 0} \sum_{r=1}^{t/h} o_3(h, (\Delta_h w)^2) . \end{aligned} \tag{7}$$

The first sum can be shown [6] to converge a.s. to

$$\int_0^t \frac{a_j^2 \psi_j(s)}{2} ds .$$

The second sum can be shown [3] to converge to 0. (For example, if $|f(s)| \leq M$ in $[0, t]$ then the sum $\sum_{r=1}^{t/h} f(rh) h (w((r+1)h) - w(rh))$ is bounded by

$$Mt \sup_t |w(t+h) - w(t)|$$

but since $w(t)$ is a.s. continuous it is also uniformly continuous and the last term converges to zero as $h \rightarrow 0$, hence the sum converges a.s. to zero).

Equation (7) becomes:

$$d\psi_j(t) = -\nu_j \psi_j(t) dt + \sum_{\substack{i=1 \\ i \neq j}}^K \nu_{ij} \psi_i(t) dt + \frac{a_j \psi_j(t)}{\beta^2} dy(t), \tag{8}$$

with the initial condition $\psi_j(0)=p_j(0)$.

Let $\phi(t) = \sum_{j=1}^K \psi_j(t)$. Then

$$d\phi(t) = \sum_{i=1}^K \frac{a_i \psi_i(t)}{\beta^2} dy(t),$$

and

$$p_j(t) = \frac{\psi_j(t)}{\sum_{i=1}^K \psi_i(t)} = \frac{\psi_j(t)}{\phi(t)}. \quad (9)$$

Equation (8) is a stochastic differential equation for $\psi_j(t)$ from which $p_j(t)$ can be obtained by (9).

The Langevin equation¹ corresponding to (8) can be derived using equation (4.30) of [5]; the result is

$$\frac{d\psi_j}{dt} = -\nu_j \psi_j(t) + \sum_{i \neq j} \nu_{ij} \psi_i(t) + \frac{1}{2} \frac{a_j^2 \psi_j(t)}{\beta^2} + \frac{a_j \psi_j(t)}{\beta^2} \frac{dy(t)}{dt} \quad (10)$$

and $dy(t)/dt$ is $x(t)$ plus “white noise”.

IV. The stochastic differential equation for $p_j(t)$.

Since (by definition of ψ_j and ϕ) $\phi(t) \neq 0$ a.s., we may apply Ito’s rule of differentiation [3] to (9):

$$\begin{aligned} dp_j(t) &= \frac{d\psi_j(t)}{\phi(t)} - \frac{\psi_j(t) d\phi(t)}{\phi^2(t)} - \frac{1}{\phi^2(t)} \frac{a_j \psi_j(t)}{\beta^2} \left(\sum_{i=1}^K \frac{a_i \psi_i(t)}{\beta^2} \right) \beta^2 dt \\ &\quad + \frac{\psi_j(t)}{\phi^3(t)} \left(\sum_{i=1}^K \frac{a_i \psi_i(t)}{\beta^2} \right)^2 \beta^2 dt. \end{aligned}$$

Substituting for $d\psi_j$ and $d\phi$, and setting $\frac{\sum_{j=1}^K a_j \psi_j(t)}{\phi(t)} = \bar{x}(t)$ we get

¹see [3] or [7]

$$\begin{aligned}
dp_j(t) &= -\nu_j p_j(t) dt + \sum_{i \neq j}^K p_i(t) \nu_{ij} dt \\
&+ \beta^{-2} (a_j - \bar{x}(t)) p_j(t) dy(t) \\
&+ \beta^{-2} \bar{x}(t) p_j(t) (a_j - \bar{x}(t)) dt \quad [\bar{x}(t) = \sum_{j=1}^K a_j p_j(t)]
\end{aligned} \tag{11}$$

which are the equations derived by Wonham. Note that as $\beta^2 \rightarrow \infty$ we get the Kolmogorov forward equation (as expected). The equations for $\psi_j(t)$ are more elegant than those for $p_j(t)$. However, the equations for $p_j(t)$ are probably more useful for applications since they ensure that the output is always in $[0, 1]$ (while $\psi_j(t)$ can be anywhere in $(0, \infty)$). It seems also that perhaps the $p_j(t)$ may have a stationary distribution while $\psi_j(t)$ may not have such a distribution.

The Langevin equation corresponding to (11) is, by eq. (4.30) of [5],

$$\begin{aligned}
\frac{dp_j(t)}{dt} &= -\nu_j p_j + \sum_{i \neq j} p_i \nu_{ij} + \frac{1}{2} p_j \beta^{-2} \left(a_j^2 - \sum_{i=1}^K a_i^2 p_i \right) \\
&+ \beta^{-2} (a_j - \bar{x}) p_j \frac{dy}{dt} .
\end{aligned} \tag{12}$$

V. Example - The random telegraph signal.

In this case $a_1 = 1, \quad a_2 = -1$

$$\nu_i = \nu_{ij} = \nu; \quad i, j = 1, 2$$

where ν is the expected number of jumps.

Let $q(t) = p_1(t) - p_2(t)$

then $\bar{x}(t) = q(t)$ and the equations of the last paragraph become

$$dq(t) = -2\nu q(t) dt - \beta^{-2} q(t)(1 - q^2(t)) dt + \beta^{-2} (1 - q^2(t)) dy(t)$$

or, equivalently

$$\begin{aligned}
dq(t) &= -2\nu q(t) dt - \beta^{-2} q(t)(1 - q^2(t)) dt + \beta^{-2} (1 - q^2(t)) x(t) dt \\
&+ \beta^{-1} (1 - q^2(t)) dw(t) .
\end{aligned}$$


The Langevin equivalent of this stochastic differential equation is given by ([5], [7])

$$\frac{dq(t)}{dt} = -2\nu q(t) + \beta^{-2}(1-q^2(t)) x(t) + \beta^{-2}(1-q^2(t)) n(t)$$


where $n(t)$ is “white noise”. Let $x(t)+n(t)=r(t)$, then we have the Riccati equation:

$$\frac{dq(t)}{dt} = -2\nu q(t) + \beta^{-2}(1-q^2(t)) r(t) \quad [r(t)=x(t)+n(t)] .$$

The physical filter to compute $q(t)$ will therefore be



or:



If, instead of the analog filter we use a digital computer we have to distinguish between two cases. Let ω_n be the cutoff frequency of the “white noise” and ω_s be the sampling frequency of the computer. Case 1: $\nu \ll \omega_n \ll \omega_s$, Case 2: $\nu \ll \omega_s \ll \omega_n$. It follows from [5] and [7] that in case 1 the computer should be programmed to solve the Langevin equation. In case 2, Maruyama’s approximation theorem is applicable [5] and the computer should be programmed to solve Ito’s equation (via Maruyama’s approximation).

An error analysis for this example is discussed in [1].

VI. Some transformations on $\psi_j(t)$.

Equation (10) can be rewritten as

$$\frac{d\psi(t)}{dt} = A \cdot \psi(t) + \begin{bmatrix} a_1 & & 0 \\ & a_2 & \\ 0 & \ddots & \\ & & a_K \end{bmatrix} \frac{(x(t)+n(t))}{\beta^2} \cdot \psi(t) \quad (10a)$$

where A is a constant matrix and ψ is the vector $(\psi_1, \dots, \psi_K)^T$.

Setting

$$\Gamma(t) = e^{-At} \cdot \psi(t)$$

we get the Langevin equation for $\Gamma(t)$:

$$\frac{d\Gamma(t)}{dt} = e^{-At} \begin{bmatrix} a_1 & & 0 \\ & a_2 & \\ 0 & \ddots & \\ & & a_K \end{bmatrix} e^{At} \frac{(x(t)+n(t))}{\beta^2} \Gamma(t) . \quad (13)$$

Setting $\theta_j(t) = \log \psi_j(t)$

hence

$$\frac{d\theta_j(t)}{dt} = -\nu_j + \frac{1}{2} \frac{a_j^2}{\beta^2} + \sum_{i \neq j} \nu_{ij} e^{\theta_i(t) - \theta_j(t)} + \frac{a_j}{\beta^2} (x(t) + n(t)) \quad (14)$$

and since θ_i does not appear in front of the last term, this is the Ito as well as the Langevin equation for $\theta_j(t)$.

VII. The prediction of $x(t)$.

The problem is now to find the probability that $x(t+h)=a_j$, $h>0$, conditioned on $\pi_0^t y(\cdot)$. The result follows directly from

$$\begin{aligned} \text{Prob} \left\{ x(t+h) \in A \mid \pi_0^t y(\cdot) \in B \right\} &= \\ &= \sum_{i=1}^K \text{Prob} \left\{ x(t)=a_i \mid \pi_0^t y(\cdot) \in B \right\} \cdot \text{Prob} \left\{ x(t+h) \in A \mid x(t)=a_i, \pi_0^t y(\cdot) \in B \right\}. \end{aligned}$$

Since $\text{Prob} \left\{ x(t+h) \mid x(t), \pi_0^t y(\cdot) \right\} = \text{Prob} \left\{ x(t+h) \mid x(t) \right\}$, it follows that (as expected)

$$\text{Prob} \left\{ x(t+h)=a_j \mid \pi_0^t y(\cdot) \right\} = \sum_{i=1}^K p_i(t) p_{ij}(h) \quad (15)$$

where $p_i(t)$ is the solution to (11) and $p_{ij}(h)$ are defined at the beginning of section I. The extension of (15) to the probability distribution of functionals on $x(s)$, $s \geq t$, conditioned on $\pi_0^t y(\cdot)$ is obvious.

VIII. Remarks.

Section I, II and the first halves of III and V follow from Wonham [1]. Instead of proceeding directly to obtain the stochastic differential equations for $p_j(t)$ as done in [1] we first derive the stochastic differential equations for $\psi_j(t)$ (section III) from which the stochastic differential equations for $p_j(t)$ are derived by a singular transformation (section IV). The equations for $\psi_j(t)$ are considerably simpler and are of a standard form (section VI). It is believed that a similar approach can be used in the case treated by Stratonovich and Kushner (where $x(t)$ is a diffusion process). The treatment in this note is restricted to $\beta = \text{const}$, the treatment in [1] is for $\beta = \beta(t)$ where $\beta(t)$ is continuously differentiable and bounded away from zero. The extension of the arguments and results of this note to $\beta = \beta(t)$ is straightforward.

A question which was left open in [1] was the problem of the realization of the results as physical “filters”. Recent work related to this problem [5], [7] gives answers to this question. Equation (4.30) of [5], which was used in this note, was derived in [5] by a heuristic argument. Unpublished calculations (for piecewise linear approximations to the Brownian motion) show that (4.30) is correct. A short discussion on the realization problem is included in section V.

References

- [1] W.M. Wonham, “Some applications of stochastic differential equations to optimal non-linear filtering”, Technical Report 64-3, Feb. 1964, RIAS, Balitmore, Maryland.
- [2] J.L. Doob Stochastic Processes, 1953.
- [3] K. Ito, “On a formula concerning stochastic differentials”, Nagoya Math. J., Vol 3, 1951, pp. 55–65.
- [4] K. Ito, “Lectures on Stochastic Processes”, Tata Inst. of Fundamental Research, Bombay, 1961, Chapter 5, pp. 172–210.
- [5] E. Wong and M. Zakai, “On the relation between ordinary and stochastic differential equations”, ERL Report 64-26 (U. of California, Berkeley) to be published in Int’l. J. of Eng. Science (1965).
- [6] E. Wong and M. Zakai, “The oscillation of stochastic integrals”, ARL Res. Rpt. No. 424, to be published in Z. fur Wahrscheinlichkeitstheorie (1965).
- [7] E. Wong and M. Zakai, “On the convergence of ordinary integrals to stochastic integrals”, ARL Res. Rpt. No. 439, to be published in Annals Math. Stat. (1965)